



Overview

The Xenopt LY2 is a high performance and low latency layer 2/3/4 Ethernet switch with 48 1/10GbE SFP+ and 4 40GbE QSFP+ ports in a compact rack unit size. The 4 40GbE provide 160Gbps to the uplink bandwidth up to the core switch. Each 40 Gigabit Ethernet port can be independently configured as 40GbE or 4 x 10GbE for total 64 ports of 10GbE.

Simplicity

The Xenopt LY2 can be managed through industry standard command-line Interface (CLI) which reduces the training and operating costs. A user friendly Web GUI is provided via a standard Web browser to manage. The LY2 also supports Simple Network Management Protocol (SNMP) both from standard MIB and private MIB for network administrator to easily configure monitor, and manage remotely. The Auto-Installation feature implemented in the LY2 helps centralized management to simplify deployment of a truly plug-and-play experience. With the evolution from IPv4 to IPv6, The LY2 is a IPv6 integrated management device.

High Availability

The Xenopt LY2 is designed for high availability from both hardware and software perspective. The key features include:

- 1+1 hot-swappable power supplies
- Out-of-band management supported
- 802.1D, 802.1w, and 802.1s supported
- Up to 8 ports per link aggregation group (LACP) and up to 64 groups
- Multi-chassis LAG (MLAG) for preventing the risks of single point failure
- Up to 32 paths ECMP routing for load balancing and redundancy
- Virtual Router Redundancy Protocol supported

High-Performance L2/L3 access deployments

With the compact 1U form factor, high density 48 1G/10G SFP+ and 4 40G QSFP+ ports in the front panel, front to back or back to front airflow design, the Xenopt LY2 is ideal for top-of-rack deployments in high-performance, highly demanding data centers. The 1.28 terabits per second switching capacity and 960Mpps forwarding rate with low power consumption ensure LY2 to be a powerful solution to aggregate high-performance servers in the data center.

Advanced IPv4 and IPv6 routing

The Xenopt LY2 is a full layer 2 and layer 3 routing switch that supports advanced IPv4 and IPv6 routing features such as RIP v1/v2, OSPF/ECMP, RIPng and OSPFv3. The multicast routing features for IGMP v1/v2/v3, DVMRP, PIM-DM/SM, MLD v1/v2 and PIM-DM6/SM6 are all supported in the LY2.

Data Center application

The Xenopt LY2 is an IEEE special DCB switch delivering a high-performance solution to integrate server edge access. The key features include:

- Congestion Notification (CN, 802.1Qau)
- Enhanced Transmission Selection (ETS, 802.1Qaz)
- Priority-based Flow Control (PFC, 802.1Qbb)
- Data Center Bridging Extension (DCBX, 802.1Qaz)
- FCoE Initiation Protocol (FIP) snooping

Product Highlight:

Performance

- 48 1/10GbE SFP+ and 4 40GbE QSFP+ ports in 1RU
- 1.28 terabits per second
- 960 million packets per second

Robust hardware

- Redundant and hot-swappable power supply
- Out-of-band management port
- 4 fixed fans

Management

- CLI/Web/SNMP, sFlow, IPv6, Auto-Installation

Layer 3 features

- RIP v1/v2, OSPF/ECMP, IGMP v1/v2/v3
- PIM-DM/SM

IPv6 support

- RIPng, OSPFv3, MLD v1/v2, PIM-DM6/SM6

Data Center application

- CN (802.1Qau), ETS (802.1Qaz)
- PFC (802.1Qbb), DCBX (802.1Qaz)
- FIP snooping

Networking LY2 specifications

Physical ports

- 48 1/10GbE SFP+ and 4 40GbE QSFP+ ports
- 1 RJ-45 out-of-band management port (10/100/1000)
- 1 RJ-45 console port

Performance

- Switching capacity: 1.28 Tbps
- Forwarding rate: 960Mpps
- Latency: 1.2 microseconds
- Memory: 2GB
- Flash: 64MB
- MAC: 128K
- Packet buffer: 9MB
- Jumbo frame: 12K

L2 features

- Auto-negotiation for port speed and duplex
- Flow control: IEEE 802.3x & back-pressure
- Switching mode: store-and-forward
- Spanning Tree Protocol:
 - 802.1D, 802.1w, & 802.1s
 - Spanning Tree Fast Forwarding
 - Edge port, Loop guard
 - BPDU filter/guard
 - Auto Edge
 - TCN guard, Root guard
- VLANs
 - IEEE 802.1Q tagged based
 - Port-based (up to 4094 VLANs)
 - Private VLAN
 - GVRP/GMRP
 - 802.1v protocol VLAN
 - Voice VLAN,
 - MAC-based VLAN
 - IP-subnet VLAN, QinQ
- VTP v1/v2
- Storm control
 - Broadcast
 - Unknown multicast
 - Unknown unicast
- IGMP snooping
 - IGMP snooping v1/v2/v3
 - IGMP v1/v2 querier
 - IGMP immediate leave
- Link Aggregation
 - 802.3ad with LACP
 - Cisco EtherChannel Like
 - Unicast/Multicast traffic balance Over trunking port (dst-ip, dst-mac, src-dst-ip, src-dst-mac, src-ip, src-mac)
- Multi-chassis LAG (MLAG)
- Link state, port backup

QoS

- Priority queues: 8 queues
- Scheduling for priority queue: WRR, Strict and hybrid (WRR+Strict)
- COS: 802.1p, IP Precedence, & DSCP
- DiffServ, port rate limit
- Auto VoIP, iSCSI optimization

Security

- Static and dynamic port security (MAC-based)
- 802.1x: port-based, MAC-based,

- auto VLAN assignment, QoS assignment, guest VLAN, unauthenticated VLAN
- ACL: L2/L3/L4
- IPv6 ACL: L3/L4
- RADIUS: authentication and accounting (up to 32 servers)
- TACACS+: authentication (up to 5 servers)
- HTTPS (AES 128-cbc, 3ES-cbc, Blowfish-cbc)
- SSH 1.5/v2.0 (AES 128-cbc, 3ES-cbc, Blowfish-cbc)
- User name and password: local authentication and remote authentication via RADIUS/TACACS+
- Denial of Service control
- Management IP filtering (SNMP/Web/Telnet/SSH)
- MAC filtering, IP Source Guard
- Dynamic ARP inspection (DAI)
- DHCP snooping

Management

- Industrial command-line interface
- CLI filtering
- Telnet/SSH
- Software download/upload: TFTP/Xmodem/FTP
- Configuration download/upload: TFTP/Xmodem/FTP
- Dual image supported
- SNMP v1/v2c/v3
- RMON 1, 2, 3 & 9
- BOOTP: client/relay
- DHCP: client/relay/option 82
- Auto-Installation
- Event/error log: local flash and remote server via system log (RFC3164)
- DNS: client/relay
- NTP/SNTP
- LLDP (802.1ab, Link Layer Discovery Protocol)
- CDP (Cisco Discovery Protocol) version 2
- Port mirroring: one to one & many to one
- sFlow (RFC 3176)
- IPv6 management:
 - IPv4/IPv6 Dual Stack
 - ICMPv6
 - ICMPv6 redirect
 - IPv6 Path MTU Discovery
 - IPv6 Neighbor Discovery
 - stateless auto-configuration
 - manual configuration
 - DHCPv6 (client)
 - SNMP/HTTP/SSH/Telnet over IPv6
 - IPv6 DNS resolver
 - IPv6 RADIUS/TACACS+ support
 - IPv6 Syslog support
 - IPv6 SNTP & NTP
 - IPv6 TFTP; IPv6 Ping

Layer 3 features

- CIDR
- ARP (static: 128 & dynamic 3968)
- Proxy ARP

- Local proxy ARP
- IRDP; static route
- Unicast Routing: RIP v1/v2, OSPF
- ECMP
- Multicast Routing: IGMP v1/v2/v3, DVMRP, PIM-DM/SM
- VRRP

IPv6 Layer 3 features

- Static route
- Unicast Routing: RIPng & OSPFv3
- Multicast Routing: MLD v1/v2, PIM-DM6/-SM6
- DHCPv6: relay & server

Data Center features

- Congestion Notification
- Enhanced Transmission Selection
- Priority-based Flow Control
- Data Center Bridging Extension
- FIP snooping

VM Tracer features

- VMware vSphere support
- VM Auto Discovery
- VM Adaptive Segmentation
- VM host view

Ethernet Virtual Bridge

- Ethernet Virtual Bridging (EVB, IEEE 802.1Qbg)

Mechanical

- Dimension (HxWxD): 42.8x435x393.7 mm
- Weight: 7.7kg(NET)

Environmental specifications

- Operating temperature: 0~45°C
- Operating humidity: 90% maximum relative humidity

Electrical

- Power consumption: 218.4W (full loading)

Safety

- UL 60950-1 (2nd Ed.)
- CSA C22.2 60950-1-07 (2nd Ed.)
- IEC 60950-1 (2005)
- EN 60950-1 (2006)

EMC

- FCC 47CFR, Part 15 Class A
- ICES-003 Class A
- EN 55022 Class A
- CISPR 22 Class A
- EN 55024
- EN 61000-3-2
- EN 61000-3-3
- EN 300 386

Environmental

- Reduction of Hazardous Substances (RoHS) 6

Order information

- LY2 (Front to Back)
- LY2 (Back to Front)

Warranty

- Limited lifetime warranty

Ordering informationⁱ

P/N	Description
Switches	
X1LY2BZZ0008	Switch, 1U, 4x40G QSFP+, (standard L2/L3 FW), dual PSU, Air Flow Direction Front to Back
X1LY2BZZ0009	Switch, 1U, 4x40G QSFP+, (standard L2/L3 FW), dual PSU, Air Flow Direction Back to Front
X1LY2BZZ000R	Switch, 1U, 4x40G QSFP+, (HW only), dual PSU, Air Flow Direction Front to Back
X1LY2BZZ000S	Switch, 1U, 4x40G QSFP+, (HW only), dual PSU, Air Flow Direction Back to Front
X1LY2BZZ000RC	Switch, 1U, 4x40G QSFP+, (Cumulus FW ⁱⁱ), dual PSU, Air Flow Direction Front to Back
X1LY2BZZ000SC	Switch, 1U, 4x40G QSFP+, (Cumulus FW ⁱⁱⁱ), dual PSU, Air Flow Direction Back to Front
Cables 10 G	
XCM-SFSFNgg	Cable, 10GbE AOC, SFP+ to SFP+, length: gg = {01 - 1m; 02 - 2m; 03 - 3m; 04 - 4m; 05 - 5m; 07 - 7m; 10 - 10m; 20 - 20m; 50 - 50m; C1 - 100m}
XCD-SFSFNgg	Cable, 10GbE Direct Attach Copper (DAC), SFP+ to SFP+, length: gg = {01 - 1m; 02 - 2m; 03 - 3m; 04 - 4m; 05 - 5m}
Cables 40 G	
XCE-QSQSNgg	Cable, 40GbE Direct Attach Copper, QSFP+ to QSFP+, length: gg = {01 - 1m; 03 - 3m; 05 - 5m}
XCM-QSQSNgg	Cable, 40GbE AOC, QSFP+ to QSFP+, length: gg = {01 - 1m; 02 - 2m; 03 - 3m; 05 - 5m; 07 - 7m; 10 - 10m; 20 - 20m; 50 - 50m; C1 - 100m}
XCD-QS4STgg	Cable, 40GbE Direct Attach Copper, QSFP+ to 4 x SFP+, length: gg = {01 - 1m; 03 - 3m; 05 - 5m }
XCM-QS4SSgg	Cable, 40GbE AOC, QSFP+ to 4 x SFP+, length: gg = {01 - 1m; 03 - 3m; 05 - 5m; 07 - 7m; 10 - 10m; 20 - 20m; 50 - 50m; C1 - 100m}
Pluggables	
XSM311-02LY	SFP, multimode, 1310nm, 1Gbps, 2km, LC, with DDMI (0 ± 70OC)
XSM851-M5LY	SFP, multimode, 850nm, 1Gbps, 500m, LC, with DDMI (0 ± 70OC)
XSBdd1-ffgh	SFP, bidirectional, dd = {27 - 1270nm; 29 - 1290nm; ... ; 61 - 1610nm}, 1Gbps, ff = {20 - 20km; 40 - 40km; 80 - 80km; C0 - 120km}, g = {L - LC, S - SC}, h = {N - no DDMI; Y - DDMI (0 ± 70OC)}
XSCdd1-ffLh	SFP, CWDM, 1Gbps, dd = {lower WL: 27 - 1270nm; ... 45 - 1450nm / upper WL: 47 - 1470nm; ... ; 61 - 1610nm}, ff = {40 - 40km; 80 - 80km; C0 - 120km; G0 - 160km; I0 - 180km; K0 - 200km}, LC, h = {N - no DDMI; Y - DDMI (0 ± 70OC)}
XSDdd1-ffLY	SFP, DWDM C-BAND, dd = {17 - 61 ITU grid channel}, 1Gbps, ff = {80 - 80km; C0 - 120km}, LC, with DDMI (0 ± 70OC)
XSUdd1-M1Rh	Copper SFP, 10/100/1000 Mbps, 0.1 (UTP-5), dd = {E1, EG}, h = {N - no DDMI; Y - DDMI (0 ± 70OC)}
XTM85A-M3LY	SFP+, multimode, 850nm, 10Gbps, 300m (OM3), LC, with DDMI (0 ± 70OC)
XSSdd1-ffLh	SFP, singlemode, dd = {31 - 1310nm; 55 - 1550nm}, 1Gbps, ff = {20 - 20km; 40 - 40km; 80 - 80km; C0 - 120km; G0 - 160km; I0 - 180km; K0 - 200km}, LC, h = {N - no DDMI; Y - DDMI (0 ± 70OC)}

XTS31A-ffLY	SFP+, singlemode, 1310nm, 10Gbps, ff = {02 - 2km; 10 - 10km; 20 - 20km; 40 - 40km}, LC, with DDMI (0 ± 70OC)
XTS55A-ffLY	SFP+, singlemode, 1550nm, 10Gbps, ff = {40 - 40km; 80 - 80km; A0 - 100km}, LC, with DDMI (0 ± 70OC)
XTBddA-ffLY	SFP+, bidirectional, dd = {27 - 1270nm; 32 - 1330nm; }, 10Gbps, ff = {10 - 10km; 20 - 20km; 40 - 40km; 60 - 60km}, LC, with DDMI (0 ± 70OC)
XTCddA-ffLY	SFP+, CWDM, dd = {27 - 1270nm; 29 - 1290nm; ... ; 61 - 1610nm}, 10Gbps, ff = {10 - 10km; 40 - 40km; 80 - 70/80km}, LC, with DDMI (0 ± 70OC)
XTDddA-ffLY	SFP+, DWDM C-BAND, dd = {17 - 61 ITU grid channel}, 10Gbps, ff = {40 - 40km; 80 - 80km*}, LC, with DDMI (0 ± 70OC)
XTDTCA-ffLY	SFP+, DWDM C-BAND, Tunable, 10Gbps, ff = {40 - 40km; 80 - 80km}, LC, with DDMI (0 ± 70OC)
XTLTLA-ffLY	SFP+, DWDM L-BAND, Tunable, 10Gbps, ff = {40 - 40km; 80 - 80km}, LC, with DDMI (0 ± 70OC)
XQM853-M1PY	QSFP+, multimode, 850nm, 40Gbps, {100m (OM3); 150m (OM4)}, MPO, with DDMI (0 ± 70OC)
XQM853-M3PY	QSFP+, multimode, 850nm, 40Gbps, {300m (OM3); 400m (OM4)}, MPO, with DDMI (0 ± 70OC)
XQS313-02PY	QSFP+, singlemode, 1310nm, 40Gbps, 2km, MPO, with DDMI (0 ± 70OC)
XQC273-ffLY	QSFP+, CWDM, 1270/1290/1310/1330nm, 40Gbps, ff = {02 - 2km; 10 - 10km; 20 - 20km; 40 - 40km}, LC, with DDMI (0 ± 70OC)
Spare_Ps	

Services

Notes:

ⁱ For accurate order specification please contact Xenopt reseller before placing an order. The content of this document is subject to change without notice. Xenopt does not guarantee errorless or outdated information.

ⁱⁱ For accurate Cumulus FW ordering part number please refer to <http://www.cumulusnetworks.com/>, or contact Xenopt Reseller.

ⁱⁱⁱ For accurate Cumulus FW ordering part number please refer to <http://www.cumulusnetworks.com/>, or contact Xenopt Reseller.

To find out more, please contact: